

AX-500



AX-500

Technical Specification

This series of products is a karaoke effector with speaker processor function, and each part of the function is independently adjustable

1. Adopt advanced 24BIT data bus and 32BIT DSP architecture

2. The music input channel is equipped with 7-segment parameter equalization

3. The microphone input channel is equipped with 15-band parametric equalization

4. The main output is equipped with 5-stage parameter equalization

5. The center, rear and ultra-low output are all equipped with 3-stage parameter equalization

6. The microphone is equipped with a 3-level feedback suppressor, which can be selected on/off

7. 16 modes can be stored in advance

8. All output channels are equipped with compressors and delayers

9. Built-in manager mode and user mode

10. Have perfect PC software, very intuitive equalizer curve graph

11. Super anti-shock circuit design to better protect your equipment

*The machine weight = 3.5 kg

